

Generator * Stor scene

systemet består af 2 DMX universer.

Fixture hænger på 3 truss.

Front truss hænger over publikum ca. 5 meter fra scenen

Midter truss sidder over scene og kan flyttes mellem scenekant og bagerste truss.

Bagerste truss (bagtæppet) kan flyttes mellem midter truss og bagvæggen.

DMX univers 1 er alt over scenen fordelt på 2 truss

Midt truss er placeret midt over scenen og indeholder 6 stk. Mover "Varytec Hero Spot 230" samt 2 stk. "Eurolite Audience blinder"

Bag truss er placeret ved bagtæppet og indeholder 6 stk. "Varytec Hero Wash 300 FC", samt 2 stk. "Varytec Hero Spot 230", én yderst i hver side

De 6 sidelamper er hvide LED fixture placeret i hver siden af scenen forrest ved scenekanten i ca. 2.5 m højde over scenen.

DMX univers 2 er front fixturer (1-8) placeret på front truss over publikum, bestående af 8 stk. FOS IQ 28x12

DMX univers 2 er front-fixturer placeret på front truss.

Univers 2 indeholder 8 stk. FOS IQ 28x12 samt 8 stk. AURON-ONE20.

DMX-adresser og fixture-navne i dette dokument følger SweetLight-kon

Gæste tekniker sørger selv for evt. converter til medbragt udstyr.

***Alt efterlades som det er modtaget.**

Afviklende lystekniker har det fulde ansvar for anlægget indtil det er afleveret til huset tekniker

Der må på ingen måde ændres eller flyttes på udstyret, heller ikke selv om det flyttes tilbage igen!!!

Overtrædelser af venue regler, eller misvedligehold vil medføre erstatnings ansvar!

Der er mulighed for at udvide universerne med f.eks. Medbragte gulvlamper fra udtag i dameside.

Der er desuden et ubenyttet ekstra univers fra FOH til scenens kongeside (5 pol XLR)

Alle fixture mærket med lys grøn farve er ikke fast monteret og skal aftales med dagen hustekniker minimum 7 dage inden show

Revideret d. 12-09-26

figurationen i fixtures.ini.

DMX univers 1

Kanal	Enhed	Formål	Model	Note
1	Moving head 1	Pan	Varytec, Hero Spot 230	<u>18 kanaler</u>
2		Pan-fine		
3		Tilt		
4		Tilt-fine		
5		Speed rotate		max - min
6		Dimmer		
7		Stroboscope		
8		Colour wheel		0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
9		Static gobo		
10		Rotatable gobo		
11		Rotate gobo		
12		Focus		
13		Zoom		
14		Prism		
15		Prism rotate		
16		Preprogramed shows		
17		Pan-tilt auto program		
18		Reset		
19	Moving head 2	Pan	Varytec, Hero Spot 230	<u>18 kanaler</u>
20		Pan-fine		
21		Tilt		
22		Tilt-fine		
23		Speed rotate		max - min
24		Dimmer		
25		Stroboscope		
26		Colour wheel		0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
27		Static gobo		
28		Rotatable gobo		
29		Rotate gobo		
30		Focus		
31		Zoom		
32		Prism		
33		Prism rotate		
34		Preprogramed shows		
35		Pan-tilt auto program		
36		Reset		
37	Moving head 3	Pan	Varytec, Hero Spot 230	<u>18 kanaler</u>
38		Pan-fine		
39		Tilt		
40		Tilt-fine		
41		Speed rotate		max - min
42		Dimmer		
43		Stroboscope		

44	Colour wheel		0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
45	Static gobo		
46	Rotatable gobo		
47	Rotate gobo		
48	Focus		
49	Zoom		
50	Prism		
51	Prism rotate		
52	Preprogramed shows		
53	Pan-tilt auto program		
54	Reset		
55	Moving head 4	Pan	Varytec, Hero Spot 230 <u>18 kanaler</u>
56		Pan-fine	
57		Tilt	
58		Tilt-fine	
59		Speed rotate	max - min
60		Dimmer	
61		Stroboscope	
62		Colour wheel	0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
63		Static gobo	
64		Rotatable gobo	
65		Rotate gobo	
66		Focus	
67		Zoom	
68		Prism	
69		Prism rotate	
70		Preprogramed shows	
71		Pan-tilt auto program	
72		Reset	
73	Moving head 5	Pan	Varytec, Hero Spot 230 <u>18 kanaler</u>
74		Pan-fine	
75		Tilt	
76		Tilt-fine	
77		Speed rotate	max - min
78		Dimmer	
79		Stroboscope	
80		Colour wheel	0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
81		Static gobo	
82		Rotatable gobo	
83		Rotate gobo	
84		Focus	
85		Zoom	
86		Prism	
87		Prism rotate	
88		Preprogramed shows	
89		Pan-tilt auto program	
90		Reset	

91	Moving head 6	Pan	Varytec, Hero Spot 230	<u>18 kanaler</u>
92		Pan-fine		
93		Tilt		
94		Tilt-fine		
95		Speed rotate		max - min
96		Dimmer		
97		Stroboscope		
98		Colour wheel		0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
99		Static gobo		
100		Rotatable gobo		
101		Rotate gobo		
102		Focus		
103		Zoom		
104		Prism		
105		Prism rotate		
106		Preprogramed shows		
107		Pan-tilt auto program		
108		Reset		
109	Blinder 1	Dimmer	Eurolite Audience Blinder 2x100W	<u>4 kanaler</u>
110		Strobe effekt		
111		COB 1		
112		COB 2		
113	Blinder 2	Dimmer	Eurolite Audience Blinder 2x100W	<u>4 kanaler</u>
114		Strobe effekt		
115		COB 1		
116		COB 2		
117	Lysdæmper	Dimmer	Lysdæmper	<u>1 kanaler</u>
118	Lysdæmper #2	Dimmer	Lysdæmper	<u>1 kanaler</u>
119	Lysdæmper #3	Dimmer	Lysdæmper	<u>1 kanaler</u>
120	Lysdæmper #4	Dimmer	Lysdæmper	<u>1 kanaler</u>
121	Lysdæmper #5	Dimmer	Lysdæmper	<u>1 kanaler</u>
122	Lysdæmper #6	Dimmer	Lysdæmper	<u>1 kanaler</u>
125	Hazer	Fan	Ukendt	<u>2 kanaler</u>
126		Smoke		Back-up, normalt ikke tilsluttet
127	CO2 hazer	Output Level	Antari CINEMA CH-1	<u>3 kanaler</u>
128		Fan level		Primær hazer
129		Heater		<u>0-127: off, 128-255 on</u>
130				
131				
132				
133				
134				
135				
136				
137				
138				
139				

140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186

Venstre side øverst	Color Marco	ADJ Flat par TW12	<u>2 kanaler</u>
	Dimmer		
Højre side øverst	Color Marco	ADJ Flat par TW12	<u>2 kanaler</u>
	Dimmer		
Venstre side midt	Cool white	ADJ CWWW 9	<u>5 kanaler</u>
	Warm white		
	Color tone		
	Strobing		
	dimmer		
Højre side midt	Cool white	ADJ CWWW 9	<u>5 kanaler</u>
	Warm white		
	Color tone		
	Strobing		
	dimmer		
Venstre side nederst	Cool white	ADJ CWWW 9	<u>5 kanaler</u>
	Warm white		
	Color tone		
	Strobing		
	dimmer		
Højre side nederst	Cool white	ADJ CWWW 9	<u>5 kanaler</u>
	Warm white		
	Color tone		
	Strobing		
	dimmer		
Hero Wash 300 FC #1	Pan	Varytec, Hero Wash 300 FC	<u>26 kanaler</u>
	Upan		
	Tilt		
	Utilt		
	pan-tilt speed		
	zoom		
	Dimmer		

187	Shutter		
188	Red		
189	Green		
190	Blue		
191	White		
192	Red		
193	Green		
194	Blue		
195	White		
196	Red		
197	Green		
198	Blue		
199	White		
200	Linear CTO -color temp		
201	Color Marco		
202	Segment pattern 1 to 18		
203	Transition		
204	Zoom automatic programme with decreasing speed, 1 (fast)...8 (slow)		
205	pan_tilt_macro		
206	Hero Wash 300 FC #2	Pan	Varytec, Hero Wash 300 FC <u>26 kanaler</u>
207	Up		
208	Tilt		
209	Utilt		
210	pan-tilt speed		
211	zoom		
212	Dimmer		
213	Shutter		
214	Red		
215	Green		
216	Blue		
217	White		
218	Red		
219	Green		
220	Blue		
221	White		
222	Red		
223	Green		
224	Blue		
225	White		
226	Linear CTO -color temp		
227	Color Marco		
228	Segment pattern 1 to 18		
229	Transition		
230	Zoom automatic programme with decreasing speed, 1 (fast)...8 (slow)		
231	pan_tilt_macro		
232	Hero Wash 300 FC #3	Pan	Varytec, Hero Wash 300 FC <u>26 kanaler</u>
233	Up		

234	Tilt		
235	Utilt		
236	pan-tilt speed		
237	zoom		
238	Dimmer		
239	Shutter		
240	Red		
241	Green		
242	Blue		
243	White		
244	Red		
245	Green		
246	Blue		
247	White		
248	Red		
249	Green		
250	Blue		
251	White		
252	Linear CTO -color temp		
253	Color Marco		
254	Segment pattern 1 to 18		
255	Transition		
256	Zoom automatic programme with decreasing speed, 1 (fast)...8 (slow)		
257	pan_tilt_macro		
258	Hero Wash 300 FC #4	Varytec, Hero Wash 300 FC	<u>26 kanaler</u>
259	Upa		
260	Tilt		
261	Utilt		
262	pan-tilt speed		
263	zoom		
264	Dimmer		
265	Shutter		
266	Red		
267	Green		
268	Blue		
269	White		
270	Red		
271	Green		
272	Blue		
273	White		
274	Red		
275	Green		
276	Blue		
277	White		
278	Linear CTO -color temp		
279	Color Marco		
280	Segment pattern 1 to 18		

281	Transition		
282	Zoom automatic programme with decreasing speed, 1 (fast)...8 (slow)		
283	pan_tilt_macro		
284	Hero Wash 300 FC #5	Pan	Varytec, Hero Wash 300 FC <u>26 kanaler</u>
285	Up		
286	Tilt		
287	Utilt		
288	pan-tilt speed		
289	zoom		
290	Dimmer		
291	Shutter		
292	Red		
293	Green		
294	Blue		
295	White		
296	Red		
297	Green		
298	Blue		
299	White		
300	Red		
301	Green		
302	Blue		
303	White		
304	Linear CTO -color temp		
305	Color Marco		
306	Segment pattern 1 to 18		
307	Transition		
308	Zoom automatic programme with decreasing speed, 1 (fast)...8 (slow)		
309	pan_tilt_macro		
310	Hero Wash 300 FC #6	Pan	Varytec, Hero Wash 300 FC <u>26 kanaler</u>
311	Up		
312	Tilt		
313	Utilt		
314	pan-tilt speed		
315	zoom		
316	Dimmer		
317	Shutter		
318	Red		
319	Green		
320	Blue		
321	White		
322	Red		
323	Green		
324	Blue		
325	White		
326	Red		
327	Green		

328	Blue		
329	White		
330	Linear CTO -color temp		
331	Color Marco		
332	Segment pattern 1 to 18		
333	Transition		
334	Zoom automatic programme with decreasing speed, 1 (fast)...8 (slow)		
335	pan_tilt_macro		
336	Moving head 7	Pan	Varytec, Hero Spot 230 <u>18 kanaler</u>
337		Pan-fine	
338		Tilt	
339		Tilt-fine	
340		Speed rotate	max - min
341		Dimmer	
342		Stroboscope	
343		Colour wheel	0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
344		Static gobo	
345		Rotatable gobo	
346		Rotate gobo	
347		Focus	
348		Zoom	
349		Prism	
350		Prism rotate	
351		Preprogramed shows	
352		Pan-tilt auto program	
353		Reset	
354	Moving head 8	Pan	Varytec, Hero Spot 230 <u>18 kanaler</u>
355		Pan-fine	
356		Tilt	
357		Tilt-fine	
358		Speed rotate	max - min
359		Dimmer	
360		Stroboscope	
361		Colour wheel	0-4:Open*14-22:Red*32-40:3000K*50-58:Green*68-76:Blue*86-94:Yellow:104-112:Turkish*122-130:Magenta*
362		Static gobo	
363		Rotatable gobo	
364		Rotate gobo	
365		Focus	
366		Zoom	
367		Prism	
368		Prism rotate	
369		Preprogramed shows	
370		Pan-tilt auto program	
371		Reset	
372			
373			
374			

375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410

411	Hero spot 230 gulv #1	Pan	Hero spot 230	18 kanaler
-----	-----------------------	-----	---------------	------------

412	Pan-fine
413	Tilt
414	Tilt-fine
415	Speed rotate
416	Dimmer
417	Stroboscope
418	Colour wheel
419	Static gobo
420	Rotatable gobo
421	Rotate gobo

422	Focus		
423	Zoom		
424	Prism		
425	Prism rotate		
426	Preprogramed shows		
427	Pan-tilt auto program		
428	Reset		
429	Hero spot 230 gulv #2	Hero spot 230	<u>18 kanaler</u>
430	Pan-fine		
431	Tilt		
432	Tilt-fine		
433	Speed rotate		
434	Dimmer		
435	Stroboscope		
436	Colour wheel		
437	Static gobo		
438	Rotatable gobo		
439	Rotate gobo		
440	Focus		
441	Zoom		
442	Prism		
443	Prism rotate		
444	Preprogramed shows		
445	Pan-tilt auto program		
446	Reset		
447	Hero spot 230 gulv #3	Hero spot 230	<u>18 kanaler</u>
448	Pan-fine		
449	Tilt		
450	Tilt-fine		
451	Speed rotate		
452	Dimmer		
453	Stroboscope		
454	Colour wheel		
455	Static gobo		
456	Rotatable gobo		
457	Rotate gobo		
458	Focus		
459	Zoom		
460	Prism		
461	Prism rotate		
462	Preprogramed shows		
463	Pan-tilt auto program		
464	Reset		
465	Hero spot 230 gulv #4	Hero spot 230	<u>18 kanaler</u>
466	Pan-fine		
467	Tilt		
468	Tilt-fine		

469	Speed rotate
470	Dimmer
471	Stroboscope
472	Colour wheel
473	Static gobo
474	Rotatable gobo
475	Rotate gobo
476	Focus
477	Zoom
478	Prism
479	Prism rotate
480	Preprogramed shows
481	Pan-tilt auto program
482	Reset

Opdateret d. 11-9-26

DMX univers 2

Kanal	Enhed	Formål	Model	Note
20	Washer gulv 1	dimmer	FOS IQ 28x12	<u>19 kanaler</u>
21		shutter		
22		Pan		
23		Pan-fine		
24		Tilt		
25		Tilt-fine		
26		Speed pan/tilt		max - min
27		Red		
28		Green		
29		Blue		
30		Withe		
31		Focus		
32		Macro color		
33		Color Temp		
34		Macro run		
35		Macro speed		
36		Dynamic rotate		
37		Dynamis rotate speed		
38		Special funktions		
39	Washer gulv 2	dimmer	FOS IQ 28x12	<u>19 kanaler</u>
40		shutter		
41		Pan		
42		Pan-fine		
43		Tilt		
44		Tilt-fine		
45		Speed pan/tilt		max - min
46		Red		
47		Green		
48		Blue		
49		Withe		

50	Focus		
51	Macro color		
52	Color Temp		
53	Macro run		
54	Macro speed		
55	Dynamic rotate		
56	Dynamis rotate speed		
57	Special funktions		
58	Front 3	dimmer	FOS IQ 28x12 <u>19 kanaler</u>
59		shutter	
60		Pan	
61		Pan-fine	
62		Tilt	
63		Tilt-fine	
64		Speed pan/tilt	max - min
65		Red	
66		Green	
67		Blue	
68		Withe	
69		Focus	
70		Macro color	
71		Color Temp	
72		Macro run	
73		Macro speed	
74		Dynamic rotate	
75		Dynamis rotate speed	
76		Special funktions	
77	Front 4	dimmer	FOS IQ 28x12 <u>19 kanaler</u>
78		shutter	
79		Pan	
80		Pan-fine	
81		Tilt	
82		Tilt-fine	

83	Speed pan/tilt		max - min
84	Red		
85	Green		
86	Blue		
87	Withe		
88	Focus		
89	Macro color		
90	Color Temp		
91	Macro run		
92	Macro speed		
93	Dynamic rotate		
94	Dynamis rotate speed		
95	Special funktions		
96	Front 5	dimmer	FOS IQ 28x12 <u>19 kanaler</u>
97		shutter	
98		Pan	
99		Pan-fine	
100		Tilt	
101		Tilt-fine	
102		Speed pan/tilt	max - min
103		Red	
104		Green	
105		Blue	
106		Withe	
107		Focus	
108		Macro color	
109		Color Temp	
110		Macro run	
111		Macro speed	
112		Dynamic rotate	
113		Dynamis rotate speed	
114		Special funktions	
115	Front 6	dimmer	FOS IQ 28x12 <u>19 kanaler</u>

116	shutter		
117	Pan		
118	Pan-fine		
119	Tilt		
120	Tilt-fine		
121	Speed pan/tilt		max - min
122	Red		
123	Green		
124	Blue		
125	Withe		
126	Focus		
127	Macro color		
128	Color Temp		
129	Macro run		
130	Macro speed		
131	Dynamic rotate		
132	Dynamis rotate speed		
133	Special funktions		
134	Washer gulv 3	FOS IQ 28x12	<u>19 kanaler</u>
135	shutter		
136	Pan		
137	Pan-fine		
138	Tilt		
139	Tilt-fine		
140	Speed pan/tilt		max - min
141	Red		
142	Green		
143	Blue		
144	Withe		
145	Focus		
146	Macro color		
147	Color Temp		
148	Macro run		

149	Macro speed		
150	Dynamic rotate		
151	Dynamis rotate speed		
152	Special funktions		
153	Washer gultv 4	FOS IQ 28x12	<u>19 kanaler</u>
154	shutter		
155	Pan		
156	Pan-fine		
157	Tilt		
158	Tilt-fine		
159	Speed pan/tilt		max - min
160	Red		
161	Green		
162	Blue		
163	Withe		
164	Focus		
165	Macro color		
166	Color Temp		
167	Macro run		
168	Macro speed		
169	Dynamic rotate		
170	Dynamis rotate speed		
171	Special funktions		

200	Front 1	AURON-ONE20	<u>37 kanaler</u>
201	Shutter		
202	Dimmer		
203	Dimmer Fine		
204	Red		
205	Red Fine		
206	Green		
207	Green Fine		
208	Blue		

208	Blue Fine
209	CTC (2700-10K)
210	Tint
211	Virtual Color Wheel
212	Zoom
213	Zoom Fine
214	Pan
215	Pan Fine
216	Tilt
217	Tilt Fine
218	Fixture control
219	LED PWM frequency
220	Beam Mix
221	FX 1
222	FX 1 adjust
223	FX 2
224	FX 2 adjust
225	FX Synchronization
226	Backlight shutter
227	Backlight dimmer
228	Backlight dimmer Fine
229	Backlight Red
230	Backlight Green
231	Backlight Blue
232	Backlight CTC
233	Backlight Tint
234	Backlight virtual color wheel
235	Backlight Mix
236	Frost Filter
237 Front 2	Shutter
238	Dimmer
239	Dimmer Fine
240	Red

AURON-ONE20

37 kanaler

241	Red Fine
242	Green
243	Green Fine
244	Blue
245	Blue Fine
246	CTC (2700-10K)
247	Tint
248	Virtual Color Wheel
249	Zoom
250	Zoom Fine
251	Pan
252	Pan Fine
253	Tilt
254	Tilt Fine
255	Fixture control
256	LED PWM frequency
257	Beam Mix
258	FX 1
259	FX 1 adjust
260	FX 2
261	FX 2 adjust
262	FX Synchronization
263	Backlight shutter
264	Backlight dimmer
265	Backlight dimmer Fine
266	Backlight Red
267	Backlight Green
268	Backlight Blue
269	Backlight CTC
270	Backlight Tint
271	Backlight virtual color wheel
272	Backlight Mix
273	Frost Filter

274 EJ INSTALLERET	Shutter	AURON-ONE20	<u>37 kanaler</u>
275	Dimmer		
276	Dimmer Fine		
277	Red		
278	Red Fine		
279	Green		
280	Green Fine		
281	Blue		
282	Blue Fine		
283	CTC (2700-10K)		
284	Tint		
285	Vitual Color Wheel		
286	Zoom		
287	Zoom Fine		
288	Pan		
289	Pan Fine		
290	Tilt		
291	Tilt Fine		
292	Fixture control		
293	LED PWM frequency		
294	Beam Mix		
295	FX 1		
296	FX 1 adjust		
297	FX 2		
298	FX 2 adjust		
299	FX Synchronization		
300	Backlight shutter		
301	Backlight dimmer		
302	Backlight dimmer Fine		
303	Backlight Red		
304	Backlight Green		
305	Backlight Blue		
306	Backlight CTC		

307	Backlight Tint		
308	Backlight virtual color wheel		
309	Backlight Mix		
310	Frost Filter		
311	EJ INSTALLERET	AURON-ONE20	<u>37 kanaler</u>
312	Dimmer		
313	Dimmer Fine		
314	Red		
315	Red Fine		
316	Green		
317	Green Fine		
318	Blue		
319	Blue Fine		
320	CTC (2700-10K)		
321	Tint		
322	Vitual Color Wheel		
323	Zoom		
324	Zoom Fine		
325	Pan		
326	Pan Fine		
327	Tilt		
328	Tilt Fine		
329	Fixture control		
330	LED PWM frequency		
331	Beam Mix		
332	FX 1		
333	FX 1 adjust		
334	FX 2		
335	FX 2 adjust		
336	FX Synchronization		
337	Backlight shutter		
338	Backlight dimmer		
339	Backlight dimmer Fine		

340	Backlight Red		
341	Backlight Green		
342	Backlight Blue		
343	Backlight CTC		
344	Backlight Tint		
345	Backlight virtual color wheel		
346	Backlight Mix		
347	Frost Filter		
348	EJ INSTALLERET Shutter	AURON-ONE20	<u>37 kanaler</u>
349	Dimmer		
350	Dimmer Fine		
351	Red		
352	Red Fine		
353	Green		
354	Green Fine		
355	Blue		
356	Blue Fine		
357	CTC (2700-10K)		
358	Tint		
359	Vitual Color Wheel		
360	Zoom		
361	Zoom Fine		
362	Pan		
363	Pan Fine		
364	Tilt		
365	Tilt Fine		
366	Fixture control		
367	LED PWM frequency		
368	Beam Mix		
369	FX 1		
370	FX 1 adjust		
371	FX 2		
372	FX 2 adjust		

373	FX Synchronization
374	Backlight shutter
375	Backlight dimmer
376	Backlight dimmer Fine
377	Backlight Red
378	Backlight Green
379	Backlight Blue
380	Backlight CTC
381	Backlight Tint
382	Backlight virtual color wheel
383	Backlight Mix
384	Frost Filter

385	EJ INSTALLERET	Shutter	AURON-ONE20	<u>37 kanaler</u>
-----	----------------	---------	-------------	--------------------------

386	Dimmer
387	Dimmer Fine
388	Red
389	Red Fine
390	Green
391	Green Fine
392	Blue
393	Blue Fine
394	CTC (2700-10K)
395	Tint
396	Vitual Color Wheel
397	Zoom
398	Zoom Fine
399	Pan
400	Pan Fine
401	Tilt
402	Tilt Fine
403	Fixture control
404	LED PWM frequency
405	Beam Mix

406	FX 1		
407	FX 1 adjust		
408	FX 2		
409	FX 2 adjust		
410	FX Synchronization		
411	Backlight shutter		
412	Backlight dimmer		
413	Backlight dimmer Fine		
414	Backlight Red		
415	Backlight Green		
416	Backlight Blue		
417	Backlight CTC		
418	Backlight Tint		
419	Backlight virtual color wheel		
420	Backlight Mix		
421	Frost Filter		
422 Front 7	Shutter	AURON-ONE20	<u>37 kanaler</u>
423	Dimmer		
424	Dimmer Fine		
425	Red		
426	Red Fine		
427	Green		
428	Green Fine		
429	Blue		
430	Blue Fine		
431	CTC (2700-10K)		
432	Tint		
433	Vitual Color Wheel		
434	Zoom		
435	Zoom Fine		
436	Pan		
437	Pan Fine		
438	Tilt		

439	Tilt Fine
440	Fixture control
441	LED PWM frequency
442	Beam Mix
443	FX 1
444	FX 1 adjust
445	FX 2
446	FX 2 adjust
447	FX Synchronization
448	Backlight shutter
449	Backlight dimmer
450	Backlight dimmer Fine
451	Backlight Red
452	Backlight Green
453	Backlight Blue
454	Backlight CTC
455	Backlight Tint
456	Backlight virtual color wheel
457	Backlight Mix
458	Frost Filter

459 Front 8

Shutter

AURON-ONE20

37 kanaler

460	Dimmer
461	Dimmer Fine
462	Red
463	Red Fine
464	Green
465	Green Fine
466	Blue
467	Blue Fine
468	CTC (2700-10K)
469	Tint
470	Vitual Color Wheel
471	Zoom

472	Zoom Fine
473	Pan
474	Pan Fine
475	Tilt
476	Tilt Fine
477	Fixture control
478	LED PWM frequency
479	Beam Mix
480	FX 1
481	FX 1 adjust
482	FX 2
483	FX 2 adjust
484	FX Synchronization
485	Backlight shutter
486	Backlight dimmer
487	Backlight dimmer Fine
488	Backlight Red
489	Backlight Green
490	Backlight Blue
491	Backlight CTC
492	Backlight Tint
493	Backlight virtual color wheel
494	Backlight Mix
495	Frost Filter

Opdateret d. 11-9-26